



How to create a VOIP Line in DoorVaani.com?

1. Login into your DoorVaani.com account.
2. You will see “My VOIP Lines” page as in the below image. You can also click on “MY DASHBOARD > VOIP Lines/Rates/Acct. Credit” menu to go to the My VOIP Lines pages. When you do not have any VOIP Lines you will see a message in red “You do not have any VOIP Lines. Please add VOIP Lines using the below inputs.”.

The screenshot shows the 'My Account' page on DoorVaani.com. The user is logged in as Anand Sharma (admin). The main content area is titled 'My VOIP Lines (SIP Domain: as1.doorvaani.com)'. It features a table with columns: Line User Name, Phone Numbers, Talktime(INR), Add Talktime(INR), Password, and Call Records. A red message indicates that no VOIP lines are currently active and provides instructions to add new lines using the provided input fields. These fields include 'VOIP Line Username' and 'Password', both marked as required, and an 'Add' button. To the right of the main content, there are two additional sections: 'My Account Credit: INR 0.00' with a 'Buy Credit' button, and 'VOIP Rates (INR / Minute)' with a 'Destination' dropdown menu.

3. Please enter a VOIP Line Username and Password pair of your choice in these inputs and then click on the “Add” button. Please note that you will not receive any username from us. You need to choose/decide on your own VOIP Line username and passwords. VOIP Line username must start with an alphabet and should be of a minimum length of 6 characters. Both username and password are case sensitive. You will see a green tick mark when you enter an available and acceptable username. You will be using this username and password when you configure your soft-phone or IP phone or IP PBX to connect to our SIP server. Your VOIP Line username is also your “sip id” and can be published by you on your business stationery and in email signatures etc., Anyone capable of calling sip ids can call you using your doorvaani.com sip id. You will receive such sip id incoming calls on the device you used to connect to our SIP server. SIP Ids are in “username@doorvaani.com” format for example “anand1@doorvaani.com”.

My VOIP Lines		(SIP Domain: as1.doorvaani.com)			
Line User Name	Phone Numbers	Talktime(INR)	Add Talktime(INR)	Password	Call Records
You do not have any VOIP Lines. Please add VOIP Lines using the below inputs.					
VOIP Line Username: *	<input type="text" value="Anand1"/>			Password: *	<input type="password" value="....."/>
			Username of your choice		Password of your choice
				<input type="button" value="Add"/>	

4. When you click on “Add” button, your VOIP Line will be added to our SIP server and then the page refreshes to show you your newly added VOIP Line under “My VOIP Lines”. You can also see your SIP Domain name in the top of the page. You will need to enter your SIP Domain or SIP server name in your Soft-phone/IP Phone/IP PBX configuration along with your VOIP Line username and password.

My VOIP Lines		(SIP Domain: as1.doorvaani.com)				Your SIP Domain/ SIP Server	
Line User Name	Phone Numbers	Talktime(INR)	Add Talktime(INR)	Password	Call Records		
Anand1	<input type="button" value="Add"/>	0.00	<input type="text"/>	<input type="button" value="Add"/>	<input type="button" value="Reset"/>	<input type="button" value="View"/>	
		Your VOIP Line					
VOIP Line Username: *	<input type="text"/>			Password: *	<input type="text"/>	<input type="button" value="Add"/>	